



Scanning with Simplicity



SAVEO-PKT2-\*\*\*\*  
Quick Setup Guide

### Package contents

- 1 x SAVEO-PKT2-\*\*\*\* scanner
- 1 x 2.4GHz USB Wireless Dongle (Plug & Play)
- 1 x USB Type-C Charging cable
- 1 x Attachable Lanyard
- 1 x 3M™ VHB™ Device Mount Plate
- 1 x Retractable Badge Reel Lanyard

### Important Safety Information

Don't put scanner, cable or accessories in places of excessively high temperature, such as exposure to direct sunlight. Don't use scanner in extremely humid conditions or in conditions of extreme temperature change. Never damage the internal rechargeable battery. Damaging the casing of the rechargeable battery might cause explosion or fire!

**TIP: KEEP SAFE / DO NOT DISCARD**

V 1.3

Saveo® and Saveo Scan™ are trademarks of Stimare Limited. All other trademarks are property of their respective owners

## Quick Setup Bluetooth HID (Default)

### 1.) Enter Pairing Mode



Bluetooth Mode

### 2.) Enable Bluetooth on your mobile device

Go to your phone's homescreen and find "Settings", then "Bluetooth" and turn Bluetooth on. Your device will search for available devices within range.

Scan this barcode to activate Bluetooth mode and to put the scanner into "Pairing mode", ready to pair to your mobile device.



After approx 20 seconds, Saveo Scan will appear as an external keyboard with a unique identifier serial number (PKT2-XXXXXXXX).

Select the scanner from "Available Devices" and wait for pairing process to complete.

Once "Connected" is displayed, your device is paired to the scanner. Your scanner is now ready to use.

**Please Note:** Devices only need to be paired once. When they are within Bluetooth range they will automatically attempt to connect to each other. If you wish to connect to another device it is recommended you first unpair this device.

-1-

## Quick Setup 2.4GHz Wireless

### 1.) Connect Via 2.4Ghz



Wireless 2.4GHz mode

Connect the included USB 2.4GHz Wireless Dongle to a free USB-A port on your computer. The dongle is a USB Class Compliant device and does not require a driver to operate in HID mode.



Plug & Play USB 2.4GHz Wireless Dongle (included)


**Please Note:** When the scanner is within range of USB 2.4Ghz receiver, the devices will automatically attempt to connect to each other until a connection is established.

### 2.) Perform a Test Scan

To test that your scanner is connected, open Notepad or a Text Editor application on your connected computer, focus the cursor, and scan the Test Barcode.



Test Barcode



You will see "Connection Successful" text populate in your text editor upon scanning the above test barcode, confirming your device is connected.

-2-

## Charging your device

### 1.) Connect the USB Type-C Cable (included)

Wake / Sleep button  
Sleeps - when held for 3 seconds.  
Wakes - on single press.



Simply connect the USB Type-C cable to the port on the bottom of the scanner and connect the USB Type-A end to a USB Type-A port (Minimum output Rating: 900mA+).

## Data Transmission Modes



Direct Mode (Default)



Memory Mode



Memory Data Upload



Total Storage Count



Clear Memory

## Bluetooth Connection Modes



Bluetooth HID (Default)

Bluetooth HID Keyboard Emulation Mode (no App required)

Bluetooth SPP Serial Port Profile Mode (requires compatible App or Driver)



Bluetooth SPP Mode



Bluetooth BLE Mode

Bluetooth BLE GATT Profile, (requires compatible App or Driver)

## Bluetooth Transmission Speed



Medium Speed (Default)



High Speed



Low Speed

## 2.4Ghz Wireless Connection Modes

**Please note:** The following 2.4GHz wireless modes require use of the Plug & Play USB 2.4GHz Wireless Dongle (included).



Plug & Play Keyboard Emulation Mode (no App required)

USB Keyboard Emu (Default)

Virtual Com Port over USB Dongle mode (requires a compatible Application or Driver)



USB VCOMM Emu

## USB Wired Connection Modes



USB Keyboard HID (Default)

Please note: USB VCOMM requires a compatible App or Driver



USB VCOMM

## Data Transmission Modes

---



Direct Mode (Default)



Memory Mode



Memory Data Upload



Total Storage Count



Clear Memory

-6-

## Audible Beeper

---



High Volume



Low Volume



Mute

## Vibration / Haptic Feedback

---



Enable (Default)



Disable

-7-

## Enter Sleep Mode / Set Standby time

---



Standby / Sleep Immediately



1 Min (Default)



5 Mins



10 Mins



30 Mins



Never

-8-

## Keyboard Languages



U.S. English Keyboard (Default)



French Keyboard



Germany Keyboard



Italy Keyboard



Portugal Keyboard



Spain Keyboard



UK Keyboard



Hungary Keyboard

## Keyboard Languages (continued)



Turkey Q Keyboard



Turkey F Keyboard

## LED Status Indicator Chart

Please refer to the table below for information regarding LED status indicator for the scanner.

### 2.4GHz RF Wireless Connection Mode

Bluetooth LED Activity	Beep Pattern	LED Activity	Indication	Working Mode
OFF	No beep	OFF	Sleeping /Power OFF	
Blue LED ON and then OFF	Beep Once	Blue LED ON and then OFF	Wake up from Sleep Mode	
White LED ON and then OFF	Beep Once	Blue LED ON and then OFF	successful scan	Normal Mode
OFF	Beep Once	Blue LED ON and then OFF	Go to sleep	
OFF	3 Beeps	Red LED Flash Three Times and Then OFF	Data transmit failed	
White LED ON and then OFF	Beep Once	Blue LED ON and then OFF, Green LED Flash	successful scan	Store Mode

### Bluetooth Connection

Bluetooth LED Activity	Beep Pattern	Read Indicator LED Activity [Square Shape]	Indication	Working Mode
OFF	No beep	OFF	Sleeping /Power OFF	
Blue LED ON and then OFF	Beep Once	Blue LED ON and then OFF	Go to sleep Mode	
Blue LED ON	Beep Once	Blue LED ON and then OFF	successful scan	Normal Mode
Blue LED Flashing	Beep Once	OFF	Bluetooth Pairing	
Solid Blue LED (No Flashing)	Beep Once	Blue LED ON and then OFF	Bluetooth Paired	
Blue LED Flashing	1 Beeps	Red LED Flashing 3 Times and then OFF	Data transmit failed	
Blue LED ON and then OFF	Beep Once	Blue LED ON and then OFF, Green LED Flash	successful scan	Store Mode

### Battery & Charging

Beep Pattern	LED Activity
5 beeps	RED LED flashing 5 Times
No beep	RED LED ON
No beep	Green LED ON

## Battery Level Status

Scan the following barcode to send the current battery level information to your device.



Check Battery Level

## System Parameters

Transmits Firmware version information to the connected device.



Get Firmware Version



Factory Reset

Returns the scanner to factory default settings

Please note: A full hard reset *Advanced Settings* document is available to download at: [saveoscan.com/downloads](http://saveoscan.com/downloads)

For Support, please

Contact us at:

Email: [inquire@saveoscan.com](mailto:inquire@saveoscan.com)

Web: [www.saveoscan.com](http://www.saveoscan.com)

US: +1-720-257-7070

UK: +44-208-099-8071

IRE: +353-1-685-4600



### Limited Warranty

Saveo provides a one year limited warranty. This warranty does not cover any product which has been subject to improper use, neglect or unauthorized repair or installation. This warranty does not cover consumable parts (Cables & batteries are consumables).